

Throttle Position Sensor Resistance Test

Meets NATEF Task: (A8-B-7) Inspect and test sensors, actuators, and circuits using a graphing multimeter (GMM)/digital storage oscilloscope (DSO); perform necessary action. (P-1)

Name _____ Date _____ Time on Task _____

Make/Model/Year _____ VIN _____ Evaluation: 4 3 2 1

_____ 1. Check service information for the specified testing procedures and resistance values of the throttle position sensor.

_____ 2. After disconnecting the electrical connectors, measure the resistance of the TP sensor using a digital multimeter (DMM) set to read ohms (Ω).

a. Measure the resistance between the terminals for the 5-volt reference and the signal resistance (ground) terminal.

_____ (should be about 1000 ohms (0.8 to 1.1 K Ω))

___ **OK** ___ **NOT OK**

b. Measure the resistance between the 5-volt reference terminal and the signal wire.

_____ ohms

c. Depress the accelerator and observe the meter. Does the resistance increase or decrease? Why?

_____ 3. Based on the tests performed, what is the necessary action? _____

